PRODUCT DATASHEET

NiMH Battery Charger (CH2PC4)

Download Instructions (multilingual)

Mini Charger

ENHANCED COMMUNICATION

 Multiple colored LED lights indicate charge status











DONE



BAD (PULSING)

VERSATILE

· Charges 1 or 2 AA or AAA NiMH batteries



SAFETY TIMER

· Ensures charger is not active for extended periods of time





Before Using Your Charger:

Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with *Energizer*_® NiMH batteries.

Product Detail:

Designation: Mini Charger

Model: CH2PC4 Color: Black

Charge Capability: "AA" (1) or (2)

"AAA" (1) or (2)

Note: Do not charge (1) "AA" and (1) "AAA"

at the same time. Please refer to the instructions for orientation diagram.

Charging Times:

(estimated)

:	Battery	Capacity	Estimated
)	(NiMH)	(mAh)	(time)
	AA	1300-2000	7-10 hrs
	AA	2000-2300	10-12 hrs
	AAA	500-800	8-10 hrs

Shutoff Mechanism: Timer: 15 hours Charging Current: "AA" 170-200mA

"AAA" 80-100mA

Trickle Charge: None

Input Rating: 100-240VAC, 50-60Hz, 3W

Typical Weight: 65 grams

Dimensions (mm): 115 x 45 x 70 (L x W x H) Safety Features: Reverse Polarity Protection

Safety Timer to Prevent Overcharge

Bad Battery Detection

Important Notice

This datasheet contains information specific to products manufactured at the time of its publication.

Contents herein do not constitute a warranty.